

- Do not use the device during an MRI or CT scan.
- The device may not work when circulation is reduced. Warm or rub the finger, or re-position the device.
- This device is a precision electronic instrument and must be repaired by qualified technical professionals. Field repair of the device is not possible. Do not attempt to open the case or repair the electronics. Opening the case may damage the device and void the warranty.
- Do not overextend the device's spring.
- A functional tester cannot be used to access the accuracy of a pulse oximeter monitor.
- Do not self-diagnose or self-medicate on the basis of the measurements without consulting your doctor. In particular, do not start taking any new medication or change the type and/or dosage of any existing medication without prior approval.
- Do not look directly inside the housing during the measurement. The red light and the invisible infra-red light in the pulse oximeter are harmful to your eyes.
- This device is not intended for use by people (including children) with restricted physical, sensory or mental skills or a lack of experience and/or a lack of knowledge, unless they are supervised by a person who has responsibility for their safety or they receive instructions from this person on how to use the device. Children should be supervised around the device to ensure they do not play with it.
- Neither of the displays for the pulse wave and pulse bar allows the strength of the pulse or circulation to be evaluated at the measurement site. Rather, they are exclusively used to display the current signal variation at the measurement site and do not enable reliable diagnostics for the pulse.

Cleaning and disinfection

1. Please clean the surface of the device before using. Wipe the device with medical alcohol (70% isopropyl alcohol) first, and then let it dry in air or clean it by dry clean fabric. When cleaning the device with water, the water temperature should be lower than 60°C
2. Using the medical alcohol to disinfect the product after use, prevent from cross infection for next time use.
3. The best storage environment of the device is - 20°C to 70°C ambient temperature and not higher than 95% relative humidity.
4. Users are advised to calibrate the device termly (or according to the calibrating program of hospital). It also can be performed at the state-appointed agent or just contact us for calibration.

- Note: 1. Do not sterilize, autoclave or immerse this device in liquid. Do not pour or spray any liquids onto the device.
2. Do not use caustic or abrasive cleaning agents, or any cleaning agent containing ammonium chloride or isopropyl alcohol.

Troubleshooting

Symptoms	Check points	Corrections
SpO2 or pulse rate cannot displayed	Applied finger improperly.	Place the finger properly and try again.
	SpO2 is too low to detect	Try again; go to consult with your physician if you are sure the device works well.
SpO2 or pulse rate are not displayed stably	Applied finger improperly.	Place the finger properly and try again.
	Finger is shaking or body is moving.	keep body steady
No display when button is pressed	Batteries run down	Replace with new batteries
	Batteries not inserted correctly.	Re-insert batteries
The display disappears suddenly	The device will auto power off when it gets no signal.	Normal
	Low battery	Replace with new batteries

⚠ Note: If the unit does not work, return it to your dealer. Under no circumstance should you disassemble and repair the unit by yourself.

Specification

SpO2	
Measuring range	35%~99%, (the resolution is 1%).
Accuracy	70%~99%: ±2%, Below 35~69%: unspecified.
Optical Sensor	Red light (wavelength is 660nm), Infrared (wavelength is 905/880nm)
Pulse	
Measuring range	30bpm~250bpm (the resolution is 1 bpm)
Accuracy	±3bpm
Power source	AAA × 2 (Alkaline)
Battery life	Continually for 16 hours with two alkaline batteries
Operating Condition	Temperature: 5°C~40°C (41°F ~ 104°F), Relative Humidity: 15-95% (non condensing), Atmospheric pressure: 700hPa ~ 1013hkPa, Attitude: -1,280 to 12,000 feet (-390m to 3,658m)
Storage Condition	Temperature: -25°C~+70°C(-13°F ~ 158°F), Relative humidity: 15-90%(non condensing), Atmospheric pressure: 700hPa ~ 1013hkPa, Attitude: -1,280 to 12,000 feet (-390m to 3,658m)
Dimensions	63.5(L) × 34(W) × 35(H) mm
Weight	About 37g (without the batteries)
Standards	IEC60601-1-2, Class B, IEC60601-1, Type BF, ISO80601-2-61, IEC60601-1-11
	Type BF applied parts
IP Classification	IP22: Protection against harmful ingress of water and particulate matter

EMC guidance and manufacturer's declaration

Recommended separation distances between portable and mobile RF communications equipment and the ME equipment The Finger-tip pulse oximeter is intended for use in an electromagnetic environment in which radiated RF disturbances are controlled. The customer or the user of the Finger-tip pulse oximeter can help prevent electromagnetic interference by maintaining a minimum distance between portable and mobile RF communications equipment (transmitters) and the Finger-tip pulse oximeter as recommended below, according to the maximum output power of the communications equipment.			
Separation distance according to frequency of transmitter / m			
Rated maximum output power of transmitter / W	150 kHz to 80 MHz, d=[3.5/ V1]√P	80 MHz to 800 MHz, d=[3.5/ E1]√P	800 MHz to 2.5 GHz, d=[3.5/ E1]√P
0.01	0.12	0.12	0.23
0.1	0.37	0.37	0.74
1	1.17	1.17	2.33
10	3.7	3.7	7.37
100	11.67	11.67	23.33
Declaration – electromagnetic emissions and immunity – for EQUIPMENT and SYSTEMS that are not LIFE-SUPPORTING and are specified for use only in a shielded location The Finger-tip pulse oximeter declaration – electromagnetic immunity The Finger-tip pulse oximeter system is intended for use in the electromagnetic environment specified below. The customer or the user of the Finger-tip pulse oximeter system should assure that it is used in such an environment.			
Immunity test		Compliance level	Electromagnetic environment-guidance
Conducted RF IEC 61000-4-6	3 Vrms 150 kHz to 80 MHz	3V	Portable and mobile RF communications equipment should be used no closer to any part of the EQUIPMENT or SYSTEM including cables, than the recommended separation distance calculated from the equation applicable to the frequency of the transmitter. Interference may occur in the vicinity of equipment marked with the following symbol. (eg)
Radiated RF IEC 61000-4-3	3V/m 80 MHz to 2.5 GHz	3V/m	
Declaration – electromagnetic immunity The Finger-tip pulse oximeter system is intended for use in the electromagnetic environment specified below. The customer or the user of the Finger-tip pulse oximeter system should assure that it is used in such an environment.			
Immunity test	IEC 60601 test level	Compliance level	Electromagnetic environment-guidance
Electrostatic discharge (ESD) IEC 61000-4-2	±6 kV contact ±8 kV air	±6 kV contact ±8 kV air	Floors should be wood, concrete or ceramic tile. If floors are covered with synthetic material, the relative humidity should be at least 30%.
Electrical fast transient/burst IEC 61000-4-4	±2 kV for power supply lines ±1 kV for input/output lines	±2 kV for power supply lines	Mains power quality should be that of a typical commercial or hospital environment.
Surge IEC 61000-4-5	± 1kV differential mode ± 2kV common mode	± 1kV differential mode ± 2kV common mode	Mains power quality should be that of a typical commercial or hospital environment.
Voltage dips, short interruptions and voltage variations on power supply input lines IEC 61000-4-11	<5% UT (>95% dip in UT) for 0,5 cycle 40% UT(60% dip in UT) for 5 cycles 70% UT(30% dip in UT) for 25 cycles <5% UT (>95% dip in UT) for 5 s	<5% UT (>95% dip in UT) for 0,5 cycle 40% UT(60% dip in UT) for 5 cycles 70% UT(30% dip in UT) for 25 cycles <5% UT (>95% dip in UT) for 5 s	Mains power quality should be that of a typical commercial or hospital environment. If the user of the EQUIPMENT or SYSTEM requires continued operation during power mains interruptions, it is recommended that the EQUIPMENT or SYSTEM be powered from an uninterruptible power supply or a battery.
Power frequency (50/60 Hz) magnetic field IEC 61000-4-8	3 A/m	3 A/m	Power frequency magnetic fields should be at levels characteristic of a typical location in a typical commercial or hospital environment.
Declaration – electromagnetic emissions The Finger-tip pulse oximeter is intended for use in the electromagnetic environment specified below. The customer or the user of the Finger-tip pulse oximeter should assure that it is used in such an environment.			
Emission test	Compliance	Electromagnetic environment-guidance	
CE emissions CISPR11	Group 1	The Finger-tip pulse oximeter uses RF energy only for its internal function. Therefore, its RF emissions are very low and are not likely to cause any interference in nearby electronic equipment.	
RF emissions CISPR 11	Class B	The Finger-tip pulse oximeter is suitable for use in all establishments, including domestic establishments and those directly connected to the public low-voltage power supply network that supplies buildings used for domestic purposes.	
Harmonic emissions IEC 61000-3-2	Class A		
Voltage fluctuations/flicker emissions IEC 61000-3-3	Complies		

 **WARNING:** The symbol on this product means that it's an electronic product and following the European directive 2012/19/EU the electronic products have to be dispose on your local recycling centre for safe treatment.

rossmax

Model: SB200



EN Fingertip Pulse Oximeter

www.rossmax.com

Warranty Card

This instrument is covered by a 1 year guarantee from the date of purchase, batteries and accessories are not included. The guarantee is valid only on presentation of the guarantee card completed by the dealer confirming date of purchase or the receipt. Opening or altering the instrument invalidates the guarantee. The guarantee does not cover damage, accidents or non-compliance with the instruction manual. Please contact your local seller/dealer or www.rossmax.com.

Customer Name: _____

Address: _____

Telephone: _____

E-mail address: _____

Product Information: _____

Date of purchase: _____

Store where purchased: _____

Introduction

Rossmax Fingertip Pulse Oximeter SB200 is used to measure arterial oxygen saturation (% SpO2) of hemoglobin and pulse rate, an important indicator of your respiratory function. It is non-invasive device intended for spot-check of adult and pediatric whose age is over 3 at home, hospital and clinics.

 Attention: Consult the accompanying documents. Please read this manual carefully before use. Please be sure to keep this manual.

ACT (Artery Check Technology)

ACT processes the SpO2 signal and determines the elasticity of blood vessel based on the derived wave form. It further classifies the vascular status into 6 levels and presents the result in an intuitive graphical interface.

	Artery and blood circulation in good condition
	Artery and blood circulation in good to average condition
	Artery and blood circulation in average condition
	Artery and blood circulation in below average condition
	Artery and blood circulation in poor condition
	Artery and blood circulation in critical condition

 Note: the classification of artery and blood circulation condition is for reference only, Please consult with your physician for further advice.

Error code for your reference


SENSOR ERROR: 	Sensor cannot be detected, return the device to your local distributor or service centre.
MEASURE ERROR: 	Signals cannot be detected, turn the device off and measure again.

AC ERROR:

AC ERROR

Weak signal for artery check, turn the device off and measure again.

Name/ Functions of each part




1. Artery check icon
2. SpO2 icon
3. Pulse rate icon
4. OLED display
5. Artery check and blood circulation icon
6. Power On/Off Button
7. Battery compartment
8. Weak Battery Mark

Installing Batteries

1. Use thumb to slide battery cover out
2. Insert or replace 2 "AAA" sized batteries down with the correct electrical polarity.

You need to replace the batteries when


1. LOW BATTERY appears on display
2. The function button is pressed and nothing appears on display



Caution: Batteries may leak or explode if used or disposed of improperly. Remove batteries if the device will be stored for long time. Do not use different types or brands of batteries at the same time. Do not mix fully charged and partially charged batteries at the same time.

Attaching the lanyard

1. Insert the narrow end of the lanyard through the holder.
2. Draw the other end of the lanyard through the loop at the narrow end and tighten.



How to use

1. Open the clip; press the Power On/Off button as ❶.
2. Information of software version appears and then finger invitation icon appears. Insert one finger(left hand middle finger is recommended), nail side up, into the finger opening of the pulse oximeter as ❷.

Note: If no finger insert, the device will auto shut off after 10 seconds


3. The display shows , pulse oximeter begins its measurement as ❸.

Note: Make sure the finger is lying flat. Do not shake and keep body steady during measurement as ❹.


4. Your SpO2 and pulse rate values will appear on the screen after few seconds and artery check result will appear on screen after 30 -60 seconds as ❺.

Note: 1. Don't remove your finger until the timer icon  is no longer on the screen.

2. If artery check result cannot be detected, "-- --" will appear on the screen.



5. When measurement is completed, the 3 parameters (SpO2, pulse rate and artery check) display and artery check display alternate automatically every 5 seconds as ❻.
6. Press button shortly to reverse the display upside down before artery check is done.
7. Press button slightly longer to turn the device off.



 Note:

1. The SpO2 sensor and photoelectric receiving tube should be arranged in a way with the subject's arteriole in a position there between.
2. Make sure the optical path is free from any optical obstacles like rubberized fabric.
3. Excessive ambient light may affect the measuring result. It includes fluorescent lamp, dual ruby light, infrared heater, direct sunlight and etc.
4. Strenuous action of the subject or extreme electrosurgical interference may also affect the accuracy.

Cautionary Notes

- This device is to be operated by trained personnel only.
- This device has no audible and it intended only for spot-checking, but not medical result evaluation.
- This device is designed to determine the percentage of arterial oxygen saturation of functional hemoglobin. Factors that may degrade pulse oximeter performance or affect the accuracy of the measurement include the following:
 - Do not apply the pulse oximeter on the same arm as a blood pressure cuff, arterial catheter or infusion line(s)
 - Excessive light, such as sunlight or direct home lighting.
 - Not steady at the site of application (e.g. trembling)
 - Moisture in the device
 - Improperly applied device
 - Finger is too large or too small to fit into the device.
 - Poor pulse quality
 - Venous pulsations
 - Anemia or low hemoglobin concentrations.
 - Cardiogreen and other intravascular dyes
 - Carboxyhemoglobin
 - Methemoglobin
 - Dysfunctional hemoglobin
 - Artificial nails or fingernail polish
 - On fingers with anatomical changes, oedemas, scars or burns.
- Using the device for long periods may cause pain for people with circulatory disorders. Reposition the device at least once every 4 hours to allow the patient's skin to breath and to check patient's condition regularly.
- Do not use the device near flammable or explosive gas mixtures.